

100 Amp 3 Phase Pagoda to Duplex Receptacles, Outdoor

PowerHOUSE™
Portable Distribution Boxes



DB100NP-AQQ-S3

Application:

This PowerHOUSE™ Pagoda portable distribution box is extremely versatile, and can be fed from a generator or panel. This box can accept up to (30) NEMA 5-20, 20 Amp Edison cords (24 on GFCI version) to power portable power tools, computers, vending machines and sound systems.



UL US LISTED
TYPE 3R

Features & Benefits:

- Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion
- Circuit breakers are mounted under hinged lid for enhanced protection
- Stackable and compact for easy storage and convenient portability
- Elevated base keeps receptacles above ground level

Specifications & Ordering Information		
Catalog Number	DB100NP-AQQ-S3	DB100NP-ABB-S3
Rating	100 Amp, 3 Phase (H,H,H,N,G), 4 Pole, 5 Wire, 120/208Y VAC	100 Amp, 3 Phase (H,H,H,N,G), 4 Pole, 5 Wire, 120/208Y VAC
Agency Listing	cULus Listed TYPE 3R	cULus Listed TYPE 3R
Environmental Rating	NEMA 3R Weather Resistant	NEMA 3R Weather Resistant
Input	(1) set of (5) 16 Series Cam-type color-coded panel mount inlets	(1) set of (5) 16 Series Cam-type color-coded panel mount inlets
Output	(12) NEMA 5-20, 20 Amp, 2 Pole, 3 Wire, 120 VAC, GFCI duplex receptacles	(15) NEMA 5-20, 20 Amp, 2 Pole, 3 Wire, 120 VAC, GFCI duplex receptacles
Feed Thru	None	None
Overcurrent Protection	(12) 20 Amp, Single Pole branch-rated circuit breakers	(15) 20 Amp, Single Pole branch-rated circuit breakers
Enclosure Type	Pagoda	Pagoda
Dimensions	14.25"L x 14.25"W x 14.15"H	14.25"L x 14.25"W x 14.15"H
Approximate Weight	32 lbs.	32 lbs.