

# RATPAC 12 x 1.2 kW SOCAPEX LUNCHBOX DIMMER



*Finally- an incandescent dimmer that also dims 120V LED tubes.*



Unlike traditional dimmers, Ratpac lunchbox dimmers are 120V LED compatible, portable, versatile, and virtually silent! Our Whisper Quiet technology enables our units to be placed right on set, reducing costly set up time and cable runs. All RatPac dimmers are ETL and CSA listed and include CRMX technology, with built-in battery to link up wireless. Allowing you control up to a quarter mile range with line of sight. You can transmit or receive with the flip

## **RATPAC 12 X 1.2 SOCAPEX LUNCHBOX DIMMER**

INPUT: 100 A BATES/CANADA, E1018 CAMLOK  
120 VAC, 50/60 HZ

OUTPUT: 2 SOCAPEX, 12 CHANNELS,  
1.2kW PER CHANNEL

### **DIMMING DEVICE**

40A DUAL SOLID STATE RELAY

### **OVERLOAD PROTECTION**

10 A RESETTABLE BREAKER

20A COURTESY OUTLET

## **CONTROL**

ANALOG: DMX 5 PIN INPUT & OUTPUT XLR

WIRELESS: CRMX RECEIVE OR TRANSMIT

MANUAL BUMP BUTTON, BI-COLOR INDICATED

DIM/NON DIM DIP SWITCHES

SELF-TERMINATING DMX STATUS QUO

## **DIMENSIONS**

12" D x 12" W x 10" H

WEIGHT: 30 LBS

## **MODEL**

756112

**"QUIET ON SET."**