



We Deliver the Power™

Lex Products Corporation
15 Progress Drive
Shelton, CT 06484
203.363.3738
203.363.3742 Fax

Lex West
11847 Sheldon Street
Sun Valley, CA 91352
818.768.4474
818.768.4040 Fax

www.lexproducts.com
info@lexproducts.com
800.643.4460

100 Amp 3 Phase Pagoda to (15) Duplex Receptacles

PowerHOUSE™
Portable Distribution Boxes



Catalog Number:
DB100A-A401520

Description:

100 Amp, 3 Phase, 4 Pole, 5 Wire, 120/208Y VAC, Pagoda Enclosure, (1) set of (5) 16 Series Cam-type color-coded panel mount inlets to (15) NEMA 5-20, 20 Amp duplex receptacles, NEMA 1 Indoor.

Typical Application:

This PowerHOUSE™ Pagoda portable distribution box is extremely versatile, and can be fed from a generator or panel. Rated for indoor use, this box can accept up to (30) NEMA 5-20, 20 Amp Edison cords to power portable power tools, computers, vending machines and sound systems.

Markets Served:

Live Events, Convention Centers, Concert Touring, Motion Picture and Television Production, Industrial

Features & Benefits

- *Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion*
- *Breakers are mounted under hinged lid for enhanced safety*
- *Stackable and compact for easy storage and convenient portability*
- *Elevated base keeps receptacles above ground level*

Specifications

Rating	100 Amp, 3 Phase (H,H,H,N,G), 4 Pole, 5 Wire, 120/208Y VAC
Environmental Rating	NEMA 1 Indoor
Input	(1) set of (5) 16 Series Cam-type color-coded panel mount inlets
Output	(15) NEMA 5-20, 20 Amp, 2 Pole, 3 Wire, 120 VAC duplex receptacles
Feed Thru	None
Overcurrent Protection	(15) 20 Amp, Single Pole branch-rated circuit breakers
Dimensions	14.5"L x 14.5"W x 13"H
Approximate Weight	32 lbs.