



We Deliver the Power™

Lex Products Corporation
15 Progress Drive
Shelton, CT 06484
203.363.3738
203.363.3742 Fax

Lex West
11847 Sheldon Street
Sun Valley, CA 91352
818.768.4474
818.768.4040 Fax

www.lexproducts.com
info@lexproducts.com
800.643.4460

100 Amp 3 Phase Pagoda to Locking Receptacles

PowerHOUSE™
Portable Distribution Boxes



Catalog Number:
DB100NP-AFF-S3

Description:

100 Amp, 3 Phase, 4 Pole, 5 Wire, 120/208Y VAC, Pagoda Enclosure, (1) set of (5) 16 Series Cam-type color-coded panel mount inlets to (5) NEMA L21-20, 20 Amp locking receptacles, NEMA 3R Weather Resistant.

Typical Application:

This box can be powered from a generator, a panel or a larger distribution box. Additionally, this box can be used at outdoor events to provide power from 20 Amp locking receptacles. The locking receptacles help prevent arcing and disconnecting under load. The receptacles can be used to power lights, effects and audio equipment.

Markets Served:

Live Events, Convention Centers, Industrial

Features & Benefits

- *Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion*
- *Breakers are mounted under hinged lid for enhanced safety*
- *Stackable and compact for easy storage and convenient portability*
- *Elevated base keeps receptacles above ground level*

Specifications

Rating	100 Amp, 3 Phase (H,H,H,N,G), 4 Pole, 5 Wire, 120/208Y VAC
Environmental Rating	NEMA 3R Weather Resistant
Input	(1) Set of (5) 16 Series Cam-type color-coded panel mount inlets
Output	(5) NEMA L21-20, 20 Amp, 3 Phase, 4 Pole, 5 Wire, 120/208Y VAC locking receptacles
Feed Thru	None
Overcurrent Protection	(5) 20 Amp, 3 Pole branch-rated circuit breakers
Dimensions	11.5"L x 11.5"W x 14"H
Approximate Weight	32 lbs.