

Lex Products Corporation 15 Progress Drive Shelton, CT 06484 203.363.3738 203.363.3742 Fax Lex West 11847 Sheldon Street Sun Valley, CA 91352 818.768.4474 818.768.4040 Fax www.lexproducts.com info@lexproducts.com 800.643.4460

100 Amp Rubber Lunchbox, Feed Thru

PowerHOUSE™
Portable Distribution Boxes



Features & Benefits

- Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion
- Breakers mounted under hinged lid for enhanced safety
- Stackable and compact for easy storage and convenient portability
- Elevated base keeps receptacles above ground level

Catalog Number: DBS100FP-B4B2

Description:

100 Amp, Single Phase, 2 Pole, 3 Wire, 120 VAC, Pagoda Jr. Enclosure, (1) 100 Amp stage pin inlet to (5) NEMA 5-20, 20 Amp duplex receptacles, Feed Thru, NEMA 1 Indoor

Typical Application:

Fed from a larger distribution box, this box provides power from a stage pin inlet to NEMA 5-20 duplex receptacles for smaller lights and related equipment. The feed thru feature allows multiple boxes to be placed along the same feed.

Markets Served:

Motion Picture and Television Production

Specifications	
Rating	100 Amp, Single Phase (H,N,G), 2 Pole, 3 Wire,120 VAC
Environmental Rating	NEMA 1 Indoor
Input	(1) 100 Amp, 2 Pole, 3 Wire, 120 VAC, stage pin inlet
Output	(5) NEMA 5-20, 20 Amp, 2 Pole, 3 Wire, 120 VAC, duplex receptacles
Feed Thru	(1) 100 Amp, 2 Pole, 3 Wire, 120 VAC, stage pin receptacle
Overcurrent Protection	(5) 20 Amp, Single Pole branch-rated circuit breakers
Dimensions	8.5"L x 8.5"W x 11"H
Approximate Weight	16 lbs.