

## 160-400 Amp Load Master™



### Features & Benefits:

- Adjustable trip setting allows the box to protect a variety of systems with different cable sizes
- Adjustable electronic circuit breaker will not nuisance trip under high ambient temperatures
- Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion
- Circuit breakers are mounted under hinged lid for enhanced protection
- Stackable and compact for easy storage and convenient portability
- Elevated base keeps receptacles above ground level

### Catalog Number:

DB400LP-AWB-S3

### Description:

160-400 Amp, 3 Phase, 4 Pole, 5 Wire, 120/208Y VAC, Pagoda Enclosure, (1) set of (5) 16 Series Cam-type color-coded panel mount inlets to (1) set of (5) 16 Series Cam-type color-coded panel mount outlets and (1) NEMA 5-20, 20 Amp duplex receptacle, TYPE 3R Rainproof. Available in 480 VAC and 600 VAC versions.

### Typical Application:

Provides overcurrent protection and a main disconnect for portable power distribution systems. The current trip setting is adjustable, allowing it to protect a variety of systems with different cable sizes.

### Markets Served:

Shipyards, Emergency/Disaster Relief, Outdoor Events, Concert Touring, Entertainment

### Specifications

<b>Rating</b>	160-400 Amp variable output, 3 Phase (H,H,H,N,G), 4 Pole, 5 Wire, 120/208Y VAC
<b>Environmental Rating</b>	TYPE 3R Rainproof
<b>Input</b>	(1) Set of (5) 16 Series Cam-type color-coded panel mount inlets
<b>Output</b>	(1) Set of (5) 16 Series Cam-type color-coded panel mount outlets protected by an adjustable circuit breaker (1) NEMA 5-20, 20 Amp, 2 Pole, 3 Wire, 120 VAC duplex receptacle
<b>Feed Thru</b>	None
<b>Overcurrent Protection</b>	(1) 400 Amp adjustable electronic breaker, 160 Amp - 400 Amp (1) 20 Amp, Single Pole branch-rated circuit breaker
<b>Enclosure</b>	Pagoda
<b>Dimensions</b>	11.5"L x 11.5"W x 14"H
<b>Weight</b>	44 lbs.

Available in 480 VAC and 600 VAC versions. Contact a Lex Products sales representative.